# product sheet 28846082

per channel 4...8  $\boldsymbol{\Omega}$ 



28846082

# FM

#### **Radio Touch**

**Technical features** 

### Functions

- countdown
- alarm clock with snooze function
- sleep timer - volume control

## Compatibility

# For loudspeakers

## **Controls and indicators**

- operation via sensor areas of the touch display
- Time and date display
- illuminated touch graphics display

#### Connectivity

- stereo FM radio with RDS display
- external audio input AUX IN

#### Main electrical features

Frequency	50/60 Hz
<b>F</b>	

# Frequency

Frequency range (radio reception)	87,5108 MHz
-----------------------------------	-------------

#### Measurement

Extension unit input	extension unit input for separate on/off switching

#### Materials

white	Colour of design line
RAL 1013 - Oyster white	RAL colour
Mixed materials	Material
velvety	Surface appearance

#### Dimensions

Insertion depth	33 mm
Dimensions of display (W x H)	35 x 28 mm

# Installation, mounting

Installation mode	single and combination mounting, screw fastening
	via supporting plate

#### Connection

Conductor cross-section	max. 2,5 mm²
Conductor cross-section (loudspeakers)	max. 1,5 mm²
Connection	with 2 loudspeaker connections
- with screw terminals	



#### Settings

- manual and automatic station search

## Equipment

- switch-on with last station

- 8 station memory, non-volatile

#### Identification

Secondary design line(s)

Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9

#### Instructions

Information text

At least one loudspeaker must be connected for operation.