


2885



## Rotary dimmer 1000 W with soft-lock, Light control, others

### Technical features

#### Main electrical features

Nominal voltage	230 V
Frequency	50 Hz

#### Voltage

Operating voltage	230 V AC
-------------------	----------

#### Fuse

Fuse	short-circuit and overload proof (electronic fuse)
------	--

#### Power

Loss power at full load	≈ 5 W
-------------------------	-------

#### Materials

Colour	not applicable
Material	Plastic/metal

#### Dimensions

Axis dimension Ø	4 mm
------------------	------

#### Incandescent bulbs control

230 V incandescent lamps and halogen lamps	100...1000 W
--	--------------

#### Installation, mounting

Installation mode	with spreader claws
-------------------	---------------------

#### Connection

Type of load	Resistive load
- with screw terminals	

#### Equipment

- phase cut-off
- with change-over pressure switch

#### Use

Differentiation characteristic 3 - Sales	with soft-lock
--	----------------

#### Safety

Halogen free	yes
--------------	-----

#### Identification

Application, usage	Light control
Main design line	Light control