



160002

### Neon lamp unit for switches/push-buttons Light control, grey

Technical features

#### Architecture

Technical version	230 V~, 0.9 mA
-------------------	----------------

#### **Controls and indicators**

- for on/off switch, 2-pole, 16 AX

### Main electrical features

Rated current 0,9 mA

#### Materials

Colour independent of design lines Grey

# **Equipment**

- for lighting and monitoring circuit
- for rockers switches double change-over
- for rockers push-buttons double change-over

### Identification

Application, usage	Light control
Main design line	Light control
Secondary design line(s)	Light control, ACCESSORIES

## Instructions

Information text

When several neon lamp units are used, the lamp current may result in malfunctioning of the relay/pulse relay.

Remedy: Switch a capacitor 230 V (1 µF per 10 mA neon lamp current) in parallel with the coil.

- Refer to the overview for the matching flush-mounted inserts.